

TAB A	MARCA:	SQUARE_D	VOLTAJE:	127
	SDI	FASES:	1	
	CAT. No:	QOX206	HILOS:	3
	MODELOS:	5	FREQ. (Hz):	60
	MONTAJE:	EMPOTRAR	TEMP. (°C):	30

TIPO DE CARGA	INSTALADA	F.D	DEMANDADA	FASES:	1=4 Av/G
CONTINUA=	982.00		764.00	NEUTRO:	1=4Av/G
DISCONTINUA=	1620.00	100.00%	1620.00	TERRA FÍSICA:	1=6 ds
INSTAL=	0.00		0.00	CARACTERIZACIÓN:	1=31mm(114")
TOTAL=	2602.00		2384.00	LONGITUD:	19
F.P=	0.9	In (Amp)=	22.78	e%	3.21
ITM PRINCIPAL=	1x40A			DESBALANCE:	0%

Mod. QOX206													CUADRO DE CARGAS "TAB-A"				110V~, 1F, 1N + 1TF				ITM= 1x40A	
CIRCUITO	DESCRIPCION	LUM-01	LUM-02	LUM-03	LUM-04	LUM-12	LUM-13	LUM-20	EXT-01	CON-01		CONTINUA	DISCONTINUA	TOTAL WATTS	TOTAL VA	AMP	D'ISTANCIA (m)	CALIBRE AWG (F~T.F.)	Caida tensión e%	ITM	FASE 1	
	W	38	40	18	8	1	0.5	29.5	120	180												
	VA	42.22	44.44	20.00	8.89	1.11	0.56	32.78	133.33	200.00												
A1	Iluminación int	2		12								292		292	324.44	2.55	14	12~12	0.29	1x15A	292.00	
A2	Iluminación ext		4		9	20						232		232	257.78	2.03	36	12~12	0.60	1x15A	232.00	
A3	Extractores								2			240		240	266.67	2.10	11	12~12	0.19	1x20A	240.00	
A4	Contactos PB									3		0.00	540	540	600.00	4.72	12	10~10	0.29	1x20A	540.00	
A5	Contactos PA									6		1080		1080	1200.00	9.45	14	10~10	0.68	1x20A	1080.00	
A6	Iluminación Andadores						23	7				218		218	242.22	1.91	5/7	12~12	0.60	1x20A	218.00	
	TOTAL=	2	4	12	9	20	23	7	2	9		982	1620	2602.00	1442.22	22.76				TOTAL=	2602	

[illegible][illegible]

TAB D		MARCA: SOLARTEC D										FASES: 3-4-5V									
		SD4										NEUTRO: 14-4V									
		FASE: 3										TIERRA FI: 4-6									
		CAY. No: NQ304L225										CANALIZAC: 1/2" mm (1/2")									
		MONTAJE: EMPOTRADO										LONGITUD: 5									
		FREC. (Hz)										DESBALAN: 5-8									
		TEMP. (°C)										CE: 0.475									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=										I ₂ (Amp): 127.32									
		T.P=																			

MARCA:		SOURCE:	VOLTAGE:	220	TIPO DE CARGA		INSTALADA		F.B		DEMANDADA FASES:		3-4 AVG			
DAT. No.:		QOC30UF	FASES:	3	CONTINUA:	1	DISCONTINUA:	2	10.000:	400.00	NEUTRO:	1-4 AVG	1-4 AVG			
MODULO:		20	TREC. (Hz):	60	MOTOR:	0.00			0.00	TIERRA FASES:	1-4	1-4 AVG	1-4 AVG			
MONTAJE:		EMPOVAR	TEMP. C°:	20	TOTAL:	4370.00			0.00	CANALIZACIÓN:	11	1-4 AVG	1-4 AVG			
					F.P.	8.70			25.40	DESBALANCE:	90					
					ITM PRINCIPAL:	366.0										
Mod. QOC30UF																
CUADRO DE CARGAS "TAB-E"																
DESCRIPCION	LUM-03	LUM-04	BOMB-1	CCOF-01	LUM-08	LUM-01	FL-01	UV-01	CONTINUA	DISCONTINUA	TOTAL WATTS	TOTAL VA	AMP	220V-, 3F, 1N + 1TF	ITM- 3x60A	
W	9	8	1120	190	175	38	190	165								
VA	10.00	8.89	1244.44	200.00	194.44	42.22	200.00	183.33								
E1	Iluminación Int	10			2				440		440	488.83	3.95	7	12	12
E2	Iluminación ext		5						40		40	44.44	0.35	7	12	12
E3	Extractor			4		1				720	720	800.00	6.30	7	10	10
E4,E8	Bomba 01			1					1120	1120	1244.44	3.27	8	8	8	0.15
E5,7,9	Bomba 02			1					1120	1120	1244.44	3.27	8	8	8	0.15
E10,12,14	Bomba 03			1					1120	1120	1244.44	3.27	7.5	8	8	0.15
E11,13,15	Bomba 04			1					1120	1120	1244.44	3.27	2.5	8	8	0.15
E 16	Filtros					2			360	360	400.00	3.15	23	10	10	0.63
E17	Reactor UV						2		330	330	366.67	2.89	22	10	10	0.55
TOTAL:		10	5	4	4	2	1	2	490	5890	6370.00	7077.78	28.60			
														% Desbalance: 13.37		